


ENDRESS

Power Generators

ESE 1506 DLS ES DI

Order No. **121012**



Main features

Alternator type	synchron
Max. Output 3~ [kVA/kW]	14,3/11,4
Max. Output 1~ [kVA/kW]	5.9/5.3
Continuous Power 3~ [kVA/kW]	13.6/10.9
Continuous Power 1~ [kVA/kW]	5.4/4.9
Nominal voltage [V]	400/230
Nominal Current [A]	19,6
Power factor cos (phi)	0,8/0,9
Frequency [Hz]	50
Protection Class [IP]	23

Engine

Engine Type	LOMBARDINI 12LD477 /23 HP
Design	2-cylinder 4-stroke
Displacement [ccm]	954
Output 3000 rpm	13,8
CO2 emissions [g / kWh]	k.A.
Fuel	Diesel
Fuel tank capacity [l]	24
Fuel consumption @ 75% PRP [L/h]	2,8
Running time @ 75% PRP	8,6
Starting system	E-Start incl. battery
Sound power level LWA [db(A)]	107
Sound pressure level LPA (7 m) [db(A)]	82
Weight in kg ca.	200
Dimensions L x W x H [mm]	960 x 641 x 667
Shockproof sockets	1 x 230 V/16 A 1 x CEE 400 V/16 A 1 x CEE 400 V/32 A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-2-19

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de



ESE 1506 DLS ES DI

Order No. 121012



Power Generators

Advantages at a glance

Does not conform to EU noise guideline 2000/14/EC

Equipment features

Large side panels protect the engine and alternator

Alternator overload protection

Compound regulated high performance generator

Starter battery 12 V

Large tank 24 litres

Possible applications

	400V	230V
Electric tools up to	10500W	6500W
Gardening or construction equipment up to	6200W	4100W
Compressors or pumps up to	5200W	3100W
Inverter welding equipment up to a dia. of 6.00 mm		

Special equipment - not retrofittable

Cable remote control (20 m)

Order No.

162 023

Accessories

Wheel kit

Order No.

161 007

выразить любую гарантию работы конкретного двигателя.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-2-19

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

